

0181x

	BLACK	0V	_____)	:	(_____	160V ORANGE	
(1)	BLACK/WHITE	100V	_____)	:	(_____	130V PINK	0.19A
	BLACK/YELLOW	110V	_____)	:	(_____	0V GREY	
	RED/YELLOW	115V	_____)	:	(_____	130V PINK	
	RED	130V	_____)	:	(_____	160V ORANGE	
(2)	BLACK	0V	_____)	:	(_____	0V YELLOW (1)	2A
	BLACK/WHITE	100V	_____)	:	(_____	6.3V YELLOW (1)	
	BLACK/YELLOW	110V	_____)	:	(_____	0V YELLOW (2)	2A
	RED/YELLOW	115V	_____)	:	(_____	6.3V YELLOW (2)	
	RED	130V	_____)	:	(_____	0V YELLOW (3)	1A
			_____)	:	(_____	6.3V YELLOW (3)	
			_____)	:	(_____	0V YELLOW (4)	1A
			_____)	:	(_____	6.3V YELLOW (4)	
			_____)	:	(_____		
	YELLOW/GREEN		_____)	:	(_____		

_____) = ELECTROSTATIC SCREEN

* FOR PRIMARY WINDING WITH SOLID CORE WIRE AND SLEEVING

If the WHITE leads are cut short please ensure the TWO wires inside the Sleeving are joined together in BOTH cases.

The solid wire inside the sleeving is coated with polyurethane and needs to be stripped away and tinned if the leads are shortened. For secondary windings with solid core leads please follow the same process.

FOR FLEXIBLE LEADS PRIMARY AND SECONDARY:

Just cut short and isolate any spare connections

NOTE: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.