

8933

BLUE	0V	_____)	:			(_____	0V ORANGE	
)	:			(0.275A
)	:			(_____	540V ORANGE	
)	:			(_____		
RED	115V	_____)	:			(_____	0V PINK	
)	:			(0.15A
)	:			(_____	160V PINK	
BLACK	0V	_____)	:			(_____	0V RED/WHITE	
)	:			(0.15A
)	:			(_____	120V RED/WHITE	
BROWN	115V	_____)	:			(_____	0V VIOLET	
GREEN/YELLOW	_____	_____)	:			(1A
Electrostatic screen			:			(-----	12V GREEN/VIOLET	
			:			(_____	24V VIOLET	
			:			(_____	0V GREY	
			:			(6.5A
			:			(-----	4V GREEN/BLUE	
			:			(_____	8V GREY	
			:			(_____	0V YELLOW (1)	
			:			(3.7A
			:			(---ct--	GREEN (1)	
			:			(_____	6.3V YELLOW (1)	
			:			(_____	0V YELLOW (1)	
			:			(0.6A
			:			(-ct--	GREEN (1)	
			:			(_____	6.3V YELLOW (1)	

For 230V: Join RED & BLACK. Use BLUE & BROWN

For 115V: Join BLUE & BLACK 0V and join RED & BROWN 115V.

If the White leads are cut short please ensure the TWO wires inside the sleeving are joined together in BOTH cases.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.