

0358

BLACK	0V	_____)				(_____	250V ORANGE	
)				(_____	0V GREY	0.1A
)				(_____	250V ORANGE	
)				(_____	18V BLUE/GREY	
)				(_____	12V YELLOW/BLACK	2A
RED	110V	_____)				(_____	0V BLUE	
)				(_____	12V YELLOW/BLACK	
BROWN	120V	_____)				(_____	18V BLUE/GREY	
)				(_____	0V YELLOW	1A
)				(_____	6.3V YELLOW	
)				(_____	0V VIOLET	
)				(_____	5V VIOLET	3A
)				(_____	0V GREEN	
)				(_____	13V GREEN	0.5A

* FOR PRIMARY WINDING WITH SOLID CORE WIRE AND SLEEVING

The solid wire inside the sleeving is coated with polyurethane and needs to be stripped away and tinned if the leads are shortened. For secondary windings with solid core leads please follow the same process.

FOR FLEXIBLE LEADS PRIMARY AND SECONDARY

Just cut short and isolate any spare connections

NOTE: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.