

7437

	BLUE	0V	_____)		(_____	395V WHITE/RED	
(1))		(_____	365V ORANGE	0.13A
	BROWN	110V	_____)		(_____	0V GREEN	
)		(_____	365V ORANGE	
(2)	BLUE	0V	_____)		(_____	395V WHITE/RED	
	BROWN	110V	_____)		(_____	0V YELLOW	
(1)	BLACK	0V	_____)		(_____	GREEN	1.5A
	RED	10V	_____)		(_____	6.3V YELLOW	
	BLACK	0V	_____)		(_____	0V VIOLET	
(2)	RED	10V	_____)		(_____	5V VIOLET	6A
)		(_____	0V PINK	
)		(_____	9V PINK	3A
)		(_____	0V GREY	
)		(_____	10V GREY	0.3A

* FOR PRIMARY WINDING WITH SOLID CORE WIRE AND SLEEVING

The solid wire inside the sleeving is coated with polyurethane and needs to be stripped away and tinned if the leads are shortened. For secondary windings with solid core leads please follow the same process.

FOR FLEXIBLE LEADS PRIMARY AND SECONDARY

Just cut short and isolate any spare connections

NOTE: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.