

7438

BLUE	0V	_____	)	(	_____	450V ORANGE	
			)	(	_____	0V WHITE	0.25A
			)	(	_____	450V ORANGE	
			)	(	_____	0V VIOLET	4A
			)	(	_____	5.1V VIOLET	
			)	(	_____	0V YELLOW (1)	10A
			)	(	-----ct	GREY (1)	
			)	(	_____	6.3V YELLOW(1)	
			)	(	_____	0V YELLOW (2)	15A
			)	(	-----ct	GREY (2)	
			)	(	_____	6.3V YELLOW (2)	
			)	(	_____	0V PINK	0.05A
			)	(	_____	100V PINK	
BROWN	240V	_____	)	(			

\* FOR PRIMARY WINDING WITH SOLID CORE WIRE AND SLEEVING

The solid wire inside the sleeving is coated with polyurethane and needs to be stripped away and tinned if the leads are shortened. For secondary windings with solid core leads please follow the same process.

FOR FLEXIBLE LEADS PRIMARY AND SECONDARY

Just cut short and isolate (INDIVIDUALLY) any spare connections

NOTE: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.