

7844

BLACK	0V	()	()	0V	VIOLET	
		()	()	410V	ORANGE	
		()	()			0.12A
BLUE	10V-	_JOIN_	()	820V	VIOLET	
		()	()	0V	YELLOW	
		()	()	_JOIN_ -ct	GREEN	
		()	()	6.3V	YELLOW	0.90A
		()	()			
WHITE	210V-	_JOIN_	()	0V	PINK (1)	
		()	()			2A
		()	()			
RED	230V-	_JOIN_	()	5V	PINK (1)	
		()	()	0V	PINK (2)	
BROWN	250V	()	()	_JOIN_ -ct	GREY	
		()	()	5V	PINK (2)	1.2A

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. Spare connections not required can be cut short, joined and isolated. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.