

8357

	BLUE	0V	_____)	:	(_____	0V ORANGE	
) :	(_____	20V PINK		
) :	(_____	350V GREY		0.3A
(1)	WHITE	110V	_____)	:	(_____	680V PINK	
) :	(_____	700V ORANGE		
	RED	120V	_____)	:	(_____	0V VIOLET	
	BLACK	0V	_____)	:	(_____	70V VIOLET	0.03A
) :	(_____	0V YELLOW (1)		5A
(2)	WHITE	110V	_____)	:	(---ct---	GREEN (1)	
) :	(_____	6.3V YELLOW (1)		
	BROWN	120V	_____)	:	(_____	0V YELLOW (2)	
) :	(---ct---	GREEN (2)		5A
) :	(_____	6.3V YELLOW (2)		
) :	(_____	0V YELLOW (3)		3A
) :	(---ct---	GREEN (3)		
) :	(_____	6.3V YELLOW (3)		

GREEN/YELLOW + CLEAR SLEEVE _____
IS ELECTROSTATIC SCREENS BETWEEN PRIMARY AND SECONDARY

For 240V: Join RED & BLACK. Use BLUE & BROWN
(Isolate both WHITES)

For 120V: Join BLUE & BLACK 0V and join RED & BROWN 120V.
(Isolate both WHITES)

For 110V: Join BLUE & BLACK 0V and join both WHITES 110V.
(Isolate RED & BLACK)

If the White leads are cut short please ensure the TWO wires are joined together in BOTH cases.