## 8502

BLUE	0V		   (	0V ORANGE	
2202	•	)	(   (	418V GREY	0·20A
(1)WHITE	110V	)  )	(   (   (	836V ORANGE	
RED	120V	)	   (   (	OV YELLOW (1)	1·50A
BLACK	0V	 	( 	6.3V YELLOW (1)	1 50A
(2)WHITE	110V	)   	   (   (   (	0V YELLOW (2) 6·3V YELLOW (2)	2A
BROWN	120V	)   ( )     	   (   (   (	0V VIOLET	3A

For 240V: Join RED & BLACK. Use BLUE & BROWN (Isolate both WHITES separately)

For 120V: Join BLUE & BLACK 0V and join RED & BROWN 120V. (Isolate both WHITES)

For 110V: Join BLUE & BLACK 0V and join both WHITES 110V. (Isolate RED & Isolate BROWN)

If the White leads are cut short please ensure the TWO wires are joined together in BOTH cases.

<u>Note:</u> A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum.