8578t

BLUE	0V		 ((400V O	RANGE	400mA
WHITE	110V)))	(((. 0V G	REY	
RED	120V)))	((400V O	RANGE	
BLACK	0V		(OV Y	ELLOW	5A
BLACK	O V)	(ct (ct	GREE	GREEN	
WHITE	110V)	((6.3V Y	ELLOW	
)		0V V	IOLET	10-
BROWN	120V)	((10V V	TOLET	10A

For 240V: Join RED & BLACK. Use BLUE & BROWN (Isolate both WHITES separately)

For 120V: Join BLUE & BLACK OV and join RED & BROWN 120V. (Isolate both WHITES)

For 110V: Join BLUE & BLACK OV and join both WHITES 110V. (Isolate RED & Isolate BROWN)

If the White leads are cut short please ensure the TWO wires inside the sleeving are joined together in BOTH cases.

<u>Note:</u> A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber Gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.