

8911

BLUE	0V	_____)	:		(_____	0V ORANGE	
)	:		(0.275A
)	:		(_____	540V ORANGE	
)	:		(_____		
RED	115V	_____)	:		(_____	0V WHITE	
)	:		(0.10A
)	:		(_____	60V WHITE	
BLACK	0V	_____)	:		(_____	0V GREY	
)	:		(6.5A
)	:		(_____	8V GREY	
BROWN	115V	_____)	:		(_____	0V VIOLET	
GREEN/YELLOW		_____)	:		(2A
Electrostatic screen			:		(-----	12V PINK	
			:		(_____	24V VIOLET	
			:		(_____	0V YELLOW	
			:		(1.8A
			:		(----ct--	GREEN	
			:		(_____	6.3V YELLOW	

For 230V: Join RED & BLACK. Use BLUE & BROWN

For 115V: Join BLUE & BLACK 0V and join RED & BROWN 115V.

If the White leads are cut short please ensure the TWO wires inside the sleeving are joined together in BOTH cases.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.