

**9395**

RED common _____ )		_____ common	GREY	
)		( _____ -50dB	BLUE-----	
)		( _____ -48dB	PINK	
)		( _____ -46dB	VIOLET	} red sleeve
)		( _____ -44dB	BROWN	
)		( _____ -42dB	GREEN	
)		( _____ -40dB	WHITE	
)		( _____ -38dB	YELLOW	
)		( _____ -36dB	BLACK	
)		( _____ -34dB	ORANGE---	
)		( _____ -32dB	BLUE-----	
)		( _____ -30dB	PINK	} orange sleeve
)		( _____ -28dB	VIOLET	
)		( _____ -26dB	BROWN	
)		( _____ -24dB	GREEN	
)		( _____ -22dB	WHITE	
)		( _____ -20dB	YELLOW	
)		( _____ -18dB	BLACK	
)		( _____ -16dB	ORANGE---	
)		( _____ -14dB	BLUE-----	
)		( _____ -12dB	PINK	} green sleeve
PINK +12db _____ )		( _____ -10dB	VIOLET	
)		( _____ - 8dB	BROWN	
)		( _____ - 6dB	GREEN	
ORANGE +6dB _____ )		( _____ - 4dB	WHITE	
)		( _____ - 2dB	YELLOW---	
)		( _____ 0dB	BLUE/YELLOW	
WHITE/ORANGE 0dB _____ )				

WHITE/ORANGE IS THE HOT SIDE OF THE PRIMARY

BLUE/YELLOW(OR ANY TAP) IS HOT FOR SECONDARY

GREY WOULD NORMALLY BE THE COLD OF THE SECONDARY

**9395 Attenuator 48 dB in 2 dB steps 0/+6dB/+12dB gain taps**

A 10k/10k transformer. 10K secondary with taps from 0 to -48dB in 2 dB steps. primary taps provided to give +6 dB or +12 dB gain. Better than 50 kHz bandwidth on all taps. Mumetal can with colour coded leads.

For more information see our website [www.sowter.co.uk](http://www.sowter.co.uk) Search 9395 and follow links