

**U067**

GREY	anode 1_____ )	( 1 _____ RED
	)	( _____ BLUE
GREEN	43% tap----- )	( 2 _____ RED
	)	( _____ BLUE
ORANGE	x 2---+HT-- _____ )	( 3 _____ RED
	)	( _____ BLUE
PINK	43% tap----- )	( 4 _____ RED
	)	( _____ BLUE
BROWN	anode 2_____ )	( _____ BLUE

**OUTPUT WINDINGS**

There are **FOUR EQUAL SECONDARY WINDINGS** which can be arranged for loads of **1, 4, 8/9 or 15/16 ohms** thus:-

1 ohm RED	4 ohm RED	8/9 ohm RED	15/16 ohm RED
(1(2(3(4	(1(2	(1(2	(1
(_(_(_(	(_(	(_(	(
BLUE	(3(4	(3	(2
	(_(	(	(
	BLUE	(4	(3
		(	(
		BLUE	(4
			(
			BLUE

**U067 Output transformer for UCL82 etc.**

9000 ohms R1a-a. 10 W at 20 Hz. 60 mA per side. For use with UCL82 20.  
Suitable for Cadet III amplifier. Dimensions may vary from original. Hz to 30 kHz.  
Size J