

0204

BLACK	0V	(_____)	(_____)	300V ORANGE (1)	
		(_____)	(_____)		0.2A
		(_____)	(-----)	0V GREY (1)	
BLUE	10V-	(__JOIN*__)	(_____)	300V ORANGE (1)	
		(_____)	(_____)	300V ORANGE (2)	
		(_____)	(_____)		0.15A
		(_____)	(-----)	0V GREY (2)	
		(_____)	(_____)	300V ORANGE (2)	
WHITE	210V-	(__JOIN*__)	(_____)	50V YELLOW/RED	
		(_____)	(-----)	0V YELLOW/BLACK	0.15A
RED	230V-	(__JOIN*__)	(_____)	50V YELLOW/RED	
		(_____)	(_____)	0V YELLOW	
BROWN	250V	(_____)	(-----ct)	GREEN	2A
		(_____)	(_____)	6.3V YELLOW	
		(_____)	(_____)	0V VIOLET (1)	
		(_____)	(_____)	5V VIOLET (1)	3A
		(_____)	(_____)	2.5V VIOLET (2)	
		(_____)	(-----)	0V PINK (2)	2A
		(_____)	(_____)	2.5V VIOLET (2)	
		(_____)	(_____)	0V VIOLET (3)	
		(_____)	(_____)	5V VIOLET (3)	2A
		(_____)	(_____)	0V VIOLET (4)	
		(_____)	(_____)	5V VIOLET (4)	2A

To obtain other inputs use as follows:
10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE= 200V

*** FOR PRIMARY WINDING WITH SOLID CORE WIRE AND SLEEVING**

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves must always be individually joined to make the primary circuit complete. Spare connections not required can be cut short, each colour joined separately and isolated. The solid wire inside the sleeving is coated with polyurethane and needs to be stripped away and tinned if the leads are shortened.

FOR FLEXIBLE LEADS PRIMARY - just cut short and isolate any spare connections

Note: A certain amount of mechanical hum is prevalent in mains transformers and rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.