0315

```
                        _______ |||| _______
BLACK   0V                     ):|||(        350V ORANGE
                               )||||(                                0.09A
                               ):|||(_______   0V GREY
                               )||||(
                               ):|||(
                               )||||(_______ 350V ORANGE
                               ):||| _______
                               )||||(        350V PINK
                               ):|||(                                0.09A
                               )||||(_______   0V YELLOW
                               ):|||(
                               )||||(
                               ):|||(_______ 350V PINK
                               )||| _______
                               ):|||(          0V VIOLET
                               )||||(                                4A
                               ):|||(_______   9V VIOLET
                               )||| _______
                               ):|||(          0V GREEN (1)
                               )||||(                                4A
                               ):|||(_______ 3.7V GREEN (1)
BROWN 240V  _______)||| _______
                               :|||(          0V GREEN (2)
                               ||||(                                4A
                               :|||(_______ 3.7V GREEN (2)
                               ||||
                               :|||
                               ||||
                               :|||
YELLOW/GREEN_________|ELECTROSTATIC SCREEN
```

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.

PDF Created with deskPDF PDF Writer - Trial :: http://www.docudesk.com