

0329

BLACK	0V	_____)	:	(_____	320V ORANGE	
)		(_____	0V GREY	0.18A
)	:	(_____		
)		(_____	320V ORANGE	
)	:	(_____	0V VIOLET	
)		(_____	CT WHITE	4A
)	:	(_____	5V VIOLET	
)		(_____	0V YELLOW (1)	
)	:	(_____	6.3V YELLOW (1)	5A
)		(_____	0V YELLOW (2)	
)	:	(_____	6.3V YELLOW (2)	5A
BROWN	240V	_____)	:	(_____	0V YELLOW (3)	
)		(_____	6.3V YELLOW (3)	0.8A
)	:	(_____	0V PINK	
)		(_____	13V PINK	2A
YELLOW/GREEN		_____)	:	(_____		
ELECTROSTATIC SCREENS (pri/ht, ht/lt)						

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.