

**0649s**

BLACK	0V	_____ )		( _____	0V WHITE/BLACK	
		_____ )		( _____		0.15A
BLUE	10V-	_____ * )		( _____	480V RED/BLACK	
		_____ )		( _____	0V PINK	3A
		_____ )		( _____	4V YELLOW	
		_____ )		( _____	0V GREEN	5A
WHITE	210V-	_____ * )		( _____	4V VIOLET	
		_____ )		( _____		
RED	230V-	_____ * )		( _____		
		_____ )		( _____		
BROWN	250V	_____ )		( _____		
		_____ )		( _____		
YELLOW/GREEN		_____ )		( _____	ELECTROSTATIC SCREEN	

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V                      BLUE/RED = 220V                      BLUE/WHITE= 200V

\* FOR PRIMARY WINDING WITH SOLID CORE WIRE AND SLEEVING

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves must always be individually joined to make the primary circuit complete. Spare connections not required can be cut short, each colour joined separately and isolated. The solid wire inside the sleeving is coated with polyurethane and needs to be stripped away and tinned if the leads are shortened.

FOR FLEXIBLE LEADS PRIMARY -

just cut short and isolate (INDIVIDUALLY) any spare connections

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.