

7779

BLACK	0V	_____)	(_____ 0V GREY	
)	(_____ 200V GREY	0.20A
)		
BLUE	10V	_____)	(_____ 0V ORANGE (1)	
)	(_____ 180V ORANGE (1)	0.20A
)		
)	(_____ 0V ORANGE (2)	
)	(_____ 180V ORANGE (2)	0.20A
)		
)	(_____ 0V YELLOW (1)	
WHITE	210V	_____)	(_____ 77V YELLOW (1)	1.5A
)		
)	(_____ 0V YELLOW (2)	
RED	230V	_____)	(_____ 77V YELLOW (2)	1.5A
)		
)	(_____ 0V YELLOW (3)	
BROWN	250V	_____)	(_____ 77V YELLOW (3)	1.5A
)		
)	(_____ 0V YELLOW (4)	
)	(_____ 77V YELLOW (4)	1.5V

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V