

7858

BLACK	0V	(	(	0V ORANGE	
		)	(	250V GREY	
		)	(		0.25A
BLUE	10V- _JOIN_	)	(	500V ORANGE	
		)	(	0V YELLOW (1)	
		)	(	_JOIN_ -ct GREEN (2)	3A
		)	(	6.3V YELLOW (1)	
WHITE	210V- _JOIN_	)	(	0V YELLOW (2)	
		)	(	_JOIN_ -ct GREEN (2)	2A
RED	230V- _JOIN_	)	(	6.3V YELLOW (2)	
		)	(	0V YELLOW (3)	
BROWN	250V	)	(	_JOIN_ -ct GREEN (3)	2A
		)	(	6.3V YELLOW (3)	
		)	(	0V VIOLET	
		)	(	5V VIOLET	2A

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V    BLUE/RED = 220V    BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. Spare connections not required can be cut short, joined and isolated. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.