

7868

BLACK	0V)	(400V ORANGE	
)	(0V GREY	
BLUE	10V-	__JOIN_	(400V ORANGE	0.25A
)	(30V PINK	
)	(0V VIOLET	
)	(30V PINK	0.05A
WHITE	210V-	__JOIN_	(3.15V YELLOW	
)	(__JOIN_ -ct GREEN	
RED	230V-	__JOIN_	(3.15V YELLOW	5A
)	(CLEAR	
BROWN	250V	_____	(5V	3A
)	(CLEAR	

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. Spare connections not required can be cut short, joined and isolated. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.