

7885

BLACK	0V	_____)				(_____	0V	ORANGE	
)				(_____			0.13A
BLUE	10V-	_JOIN_				(_____	350V	GREY	
)				(_____			
)				(_____	700V	ORANGE	
)				(_____			
)				(_____	0V	YELLOW	
)				(_____	ct	GREEN	
)				(_____			3A
WHITE	210V-	_JOIN_				(_____	6.3V	YELLOW	
)				(_____			
)				(_____	0V	VIOLET (1)	
)				(_____	ct	PINK	
)				(_____			4A
RED	230V-	_JOIN_				(_____	5V	VIOLET (1)	
)				(_____			
)				(_____	0V	VIOLET (2)	
BROWN	250V	_____)				(_____	5A	VIOLET (2)	4A

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.