

8060

BLACK	0V	_____)	(_____	0V ORANGE	
)	(_____	340V PINK	
BLUE	10V-	_JOIN_)	(_____	680V ORANGE	0.20A
)	(_____	0V VIOLET	
)	(_____		0.01A
)	(_____	65V VIOLET	
WHITE	210V-	_JOIN_)	(_____	0V YELLOW	
)	(_____	_JOIN_ -ct GREEN	6A
RED	230V-	_JOIN_)	(_____	6.3V YELLOW	
)	(_____		
BROWN	250V	_____)	(_____		

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. Spare connections not required can be cut short, joined and isolated. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.