

8111

BLACK	0V)	(0V ORANGE	
)	(
BLUE	10V-	_JOIN_	(325V GREY	0.20A
)	(
)	(650V ORANGE	
)	(
)	(0V VIOLET	0.05A
)	(
WHITE	210V-	_JOIN_	(150V VIOLET	
)	(
)	(0V PINK(1)	1.2A
RED	230V-	_JOIN_	(5V PINK(1)	
)	(
)	(
BROWN	250V	_____	(0V PINK(2)	1.2A
)	(
)	(5V PINK(2)	
)	(
)	(0V YELLOW	
)	(
)	(ct GREEN	1.2A
)	(
)	(6.3V YELLOW	

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. Spare connections not required can be cut short, joined and isolated. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.