

**8145**

BLACK	0V	_____ )	( _____	0V ORANGE	
		)	( _____	25V PINK	
BLUE	10V-	_JOIN_ )	( _____		
		)	( _____	375V GREY	0.10A
		)	( _____	725V PINK	
WHITE	210V-	_JOIN_ )	( _____	750V ORANGE	
		)	( _____	0V ORANGE/YELLOW	
RED	230V-	_JOIN_ )	( _____	ct_ GREEN/YELLOW	
		)	( _____		
BROWN	250V	_____ )	( _____	550V ORANGE/GREEN	0.06A
		)	( _____	0V VIOLET	
		)	( _____	5V VIOLET	3.0A
		)	( _____	0V YELLOW	
		)	( _____	ct_ GREEN	5A
		)	( _____	12.6V YELLOW	

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V    BLUE/RED = 220V    BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.