

8223

BLACK	0V	_____)	(_____	0V GREY	
)	(_____		0.20A
)	(_____	375V ORANGE	
BLUE	10V- _JOIN_)	(_____		
)	(_____	750V GREY	
)	(_____	0V PINK	3A
)	(_____	5V PINK	
)	(_____	0V YELLOW (1)	2.50A
WHITE	210V- _JOIN_)	(_____		
)	(_____	ct GREEN (1)	
)	(_____	2.5V YELLOW (1)	
RED	230V- _JOIN_)	(_____	0V YELLOW (2)	2.50A
)	(_____	ct GREEN (2)	
)	(_____	2.5V YELLOW (2)	
BROWN	250V	_____)	(_____	0V VIOLET	1A
)	(_____	ct CLEAR	
)	(_____	6V VIOLET	

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.