

8225

BLACK	0V	_____)	(_____ 0V ORANGE	
)	(_____ 360V GREY	0.24A
BLUE	10V-	_JOIN_)	(_____ 720V ORANGE	
)	(_____ 0V YELLOW (1)	4A
)	(_____ 6.3V YELLOW (1)	
WHITE	210V-	_JOIN_)	(_____ 0V YELLOW (2)	4A
)	(_____ 6.3V YELLOW (2)	
RED	230V-	_JOIN_)	(_____ 0V YELLOW	1.6A
)	(_____ ct GREEN	
BROWN	250V	_____)	(_____ 6.3V YELLOW	
)	(_____ 0V VIOLET	0.2A
)	(_____ 70V VIOLET	

To obtain other inputs use as follows:
10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.