

8257

BLACK	0V	_____)		(_____	0V ORANGE	
)		(_____		0.08A
)		(_____	250V GREY	
BLUE	10V-	_JOIN_)		(_____		
)		(_____	500V ORANGE	
)		(_____	0V VIOLET (1)	2A
)		(_____	4V VIOLET (1)	
)		(_____	0V VIOLET (2)	2A
WHITE	210V-	_JOIN_)		(_____	4V VIOLET (2)	
)		(_____	0V VIOLET (3)	2A
)		(_____	4V VIOLET (3)	
RED	230V-	_JOIN_)		(_____		
)		(_____		
BROWN	250V	_____)		(_____		

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.