

8267

BLACK	0V	_____)	(_____	0V GREEN	
)	(2A
BLUE	10V-	_JOIN_	(_____	13V GREEN	
)	(_____	0V VIOLET (1)	2A
)	(_____	5V VIOLET (1)	
WHITE	210V-	_JOIN_	(_____	0V VIOLET (2)	2A
)	(_____	5V VIOLET (2)	
RED	230V-	_JOIN_	(_____	0V VIOLET (3)	2A
)	(_____	5V VIOLET (3)	
BROWN	250V	_____)	(_____		

To obtain other inputs use as follows:
10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum.