

8268

BLACK	0V	_____)	(_____	0V ORANGE	
)	(_____	360V GREY	0.24A
BLUE	10V-	_JOIN_)	(_____		
)	(_____	720V ORANGE	
)	(_____	0V PINK	
)	(_____	150V PINK	0.15A
WHITE	210V-	_JOIN_)	(_____	0V GREEN (1)	
)	(_____	10V GREEN (1)	3.25A
RED	230V-	_JOIN_)	(_____	0V GREEN (2)	
)	(_____	10V GREEN (2)	3.25A
BROWN	250V	_____)	(_____	0V CLEAR	
)	(---ct---	YELLOW	1.3A
)	(_____	12.6V CLEAR	
)	(_____	0V VIOLET	
)	(_____	5V VIOLET	3A

To obtain other inputs use as follows:
10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum.