

8300

BLACK	0V	_____)	(_____	0V GREY	
)	(_____	350V PINK	
BLUE	10V-	_JOIN_)	(_____		0.15A
)	(_____	700V GREY	
)	(_____	0V VIOLET (1)	
)	(_____	ct_ YELLOW (1)	
WHITE	210V-	_JOIN_)	(_____	6.3V VIOLET (1)	3A
)	(_____	0V VIOLET (2)	
RED	230V-	_JOIN_)	(_____	ct_ YELLOW (2)	
)	(_____	6.3V VIOLET (2)	3A
BROWN	250V	_____)	(_____	0V ORANGE	
)	(_____	ct_ GREEN	
)	(_____	5V ORANGE	3A

To obtain other inputs use as follows:
 10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.