

8326

BLACK	0V	_____)	(_____	0V ORANGE (1)	
)	(_____		0.30A
)	(_____	350V ORANGE (1)	
BLUE	10V-	_JOIN_)	(_____	0V ORANGE (2)	
)	(_____	350V ORANGE (2)	0.30A
)	(_____	0V VIOLET	
)	(_____	50V VIOLET	0.20A
WHITE	210V-	_JOIN_)	(_____	0V YELLOW (1)	
)	(_____	6.3V YELLOW (1)	4A
RED	230V-	_JOIN_)	(_____	0V YELLOW (2)	
)	(_____	6.3V YELLOW (2)	4A
BROWN	250V	_____)	(_____		

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.