

8536

BLACK	0V	(	(	0V GREY	
		)	(		0.26A
BLUE	10V- __JOIN__	)	(	10V VIOLET	
		)	(		
		)	(	160V GREEN	
		)	(	0V ORANGE	
		)	(		0.15A
		)	(	290V ORANGE	
WHITE	210V- __JOIN__	)	(	0V YELLOW	
		)	(		1.5A
		)	(	6.3V YELLOW	
RED	230V- __JOIN__	)	(	0V PINK	
		)	(		3.5A
		)	(	12.6V PINK	
BROWN	250V	)	(	0V WHITE/RED	
		)	(		0.1A
		)	(	90V WHITE/RED	

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V      BLUE/RED = 220V      BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum.