

8557

BLACK	0V	_____)	(_____	0V ORANGE	
)	(_____	250V GREY	0.20A
BLUE	10V - _JOIN_	_____)	(_____	500V ORANGE	
)	(_____	0V YELLOW	3A
)	(_____	6.3V YELLOW	
WHITE	210V - _JOIN_	_____)	(_____	0V GREEN (1)	3A
)	(_____ct	PINK (1)	
RED	230V - _JOIN_	_____)	(_____	2.5V GREEN (1)	
)	(_____	0V GREEN (2)	3A
BROWN	250V	_____)	(_____ct	PINK (2)	
)	(_____	2.5V GREEN (2)	
)	(_____	0V VIOLET	2A
)	(_____	5V VIOLET	

To obtain other inputs use as follows:
10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum.