

8565

BLACK	0V	_____)	(_____	0V ORANGE	
)	(_____		0.10A
BLUE	10V-	_JOIN_	(_____	390V GREY	
)	(_____		
)	(_____	780V ORANGE	
)	(_____	0V YELLOW	4A
)	(_____	6.3V YELLOW	
WHITE	210V-	_JOIN_	(_____	0V VIOLET	3A
)	(_____	5V VIOLET	
RED	230V-	_JOIN_	(_____	0V PINK	3A
)	(_____	4V PINK	
BROWN	250V	_____)	(_____		

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V **BLUE/RED = 220V** **BLUE/WHITE = 200V**

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum.