

8601

BLACK	0V	_____)	(_____ 0V VIOLET (1)	
)	(7.5A
BLUE	10V-	_____)	(-----1.25V GREY (1)	
		JOIN)	(
)	(
)	(----- 2.5V YELLOW (1)	
)	(
)	(
)	(-----3.75V GREY/BLUE (1)	
)	(
WHITE	210V-	_____)	(_____ 5V VIOLET/BLUE (1)	
		JOIN)	(_____ 0V VIOLET (2)	7.5A
)	(
)	(-----1.25V GREY (2)	
RED	230V-	_____)	(
		JOIN)	(
)	(
)	(----- 2.5V YELLOW (2)	
BROWN	250V	_____)	(
)	(
)	(-----3.75V GREY/BLUE (2)	
)	(
)	(_____ 5V VIOLET/BLUE (2)	

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V
BLUE/RED = 220V
BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum.