

8669

BLACK	0V	_____ )	( _____	ORANGE	
		)	(		
BLUE	10V-	_JOIN_ )	( _____	ct_GREY	650V @ 0.2A
		)	(		
		)	(		
		)	(		
		)	( _____	ORANGE	
WHITE	210V-	_JOIN_ )	( _____	YELLOW	
		)	(		
		)	(		6.3V @ 5A
RED	230V-	_JOIN_ )	( _____	YELLOW	
		)	(		
BROWN	250V	_____ )	( _____	PINK	70V @ 0.05A
		)	( _____	PINK	
		)	( _____	VIOLET	5V @ 3A
		)	(		
		)	( _____	VIOLET	

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V      BLUE/RED = 220V      BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber Gasket or similar material is worth fitting to quieten this hum to its' minimum.