



**8821** for 120V/120V at 1.8A 1:1 Ratio



For 120V: Join BLUE & BLACK 0V and join RED & BROWN 120V.

**8821** for 240V/120V at 1.8A 2:1 Ratio



For 240V: Join RED & BLACK. Use BLUE & BROWN

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.