

8962

BLACK	0V	()	()	325V ORANGE	
		()	()		0.10A
BLUE	10V-	()	()	260V PINK	
	JOIN*	()	()	0V GREY	
		()	()	260V PINK	
		()	()	325V ORANGE	
		()	()	0V VIOLET	
WHITE	210V-	()	()	5V VIOLET	2A
	JOIN*	()	()	0V YELLOW/GREY (1)	
RED	230V-	()	()	3.2V GREEN (1)	1.2A
	JOIN*	()	()	6.3V YELLOW (1)	
BROWN	250V	()	()	8V GREY/YELLOW (1)	
		()	()	0V YELLOW/GREY (2)	
		()	()	3.2V GREEN (2)	1.5A
		()	()	6.3V YELLOW (2)	
		()	()	8V GREY/YELLOW (2)	

To obtain other inputs use as follows:
10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V

BLUE/RED = 220V

BLUE/WHITE= 200V

*** FOR PRIMARY WINDING WITH SOLID CORE WIRE AND SLEEVING**

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. **Spare connections not required** can be cut short, **each colour joined separately and isolated**. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.

FOR FLEXIBLE LEADS PRIMARY - just cut short and isolate any spare connections

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.