

9242

BLACK	0V	_____)	(_____	375V ORANGE	
)	(_____	235V PINK	0.30A
)	(_____	0V GREY	
)	(_____	235V PINK	
)	(_____	375V ORANGE	
)	(_____	0V VIOLET (1)	6A
RED	230V	_____)	(_____	5V VIOLET (1)	
)	(_____	0V VIOLET (2)	1.5A
)	(_____	5V VIOLET (2)	
)	(_____	0V VIOLET (3)	1.5A
)	(_____	5V VIOLET (3)	
)	(_____	0V WHITE/RED (1)	0.6A
)	(_____	22V WHITE/RED (1)	
)	(_____	0V WHITE/RED (2)	0.6A
)	(_____	22V WHITE/RED (2)	

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.