

9434

	BLUE	0V	_____)		(_____	0V GREY	
)		(_____		1A
)		(_____	330V PINK/BLACK	
(1)	WHITE	110V	_____)		(_____	340V YELLOW/BLACK	
)		(_____	350V GREEN/RED	
)		(_____	360V YELLOW/RED	
	RED	120V	_____)		(_____	370V ORANGE	
)		(_____		
	BLACK	0V	_____)		(_____	3.3V PINK	
)		(_____		10A
(2)	WHITE	110V	_____)		(_____	0V YELLOW	
)		(_____		
)		(_____	3.3V PINK	
	BROWN	120V	_____)		(_____		

For 240V: Join RED & BLACK. Use BLUE & BROWN
(Isolate both WHITES separately)

For 120V: Join BLUE & BLACK 0V and join RED & BROWN 120V.
(Isolate both WHITES)

For 110V: Join BLUE & BLACK 0V and join both WHITES 110V.
(Isolate RED & Isolate BROWN)

If the White leads are cut short please ensure the TWO wires inside the sleeving are joined together in BOTH cases.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.

