

9681

BLACK	0V	_____)	(_____	275V ORANGE	
)	(_____	0V GREY	
BLUE	10V--	_JOIN_)	(_____	275V ORANGE	0.15A
)	(_____	3.15V YELLOW (1)	
)	(_____	0V GREEN (1)	3.3A
)	(_____	3.15V YELLOW (1)	
WHITE	210V--	_JOIN_)	(_____	3.15V YELLOW (2)	
)	(_____	0V GREEN (2)	1.2A
RED	230V--	_JOIN_)	(_____	3.15V YELLOW (2)	
)			
BROWN	250V	_____)			

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V
 BLUE/RED = 220V
 BLUE/WHITE = 200V

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. Spare connections not required can be cut short, joined and isolated. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.