

M012

BLACK	0V	_____)	(_____	0V ORANGE	
)	(_____		0.43A
BLUE	10V	_____)	(_____	330V ORANGE	
)	(_____		
)	(_____	0V YELLOW (1)	
)	(_ct_ _____	GREEN (1)	
)	(_____		4A
)	(_____	6.3V YELLOW (1)	
WHITE	210V	_____)	(_____	0V YELLOW (2)	
)	(_ct_ _____	GREEN (2)	
)	(_____		4A
RED	230V	_____)	(_____	6.3V YELLOW (2)	
)	(_____		
BROWN	250V	_____)	(_____		

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V
BLUE/RED = 220V
BLUE/WHITE = 200V