

M056

BLACK	0V	_____)					(_____	0V GREY	
)					(___ct___	VIOLET	
BLUE	10V--	_JOIN_)					(_____	750V GREY	0.50A
)					(_____	0V YELLOW (1)	4A
)					(___JOIN_ -ct	GREEN (1)	
)					(_____	6.3V YELLOW (1)	
WHITE	210V--	_JOIN_)					(_____	0V YELLOW (2)	4A
)					(___JOIN_ -ct	GREEN (2)	
)					(_____	6.3V YELLOW (2)	
RED	230V--	_JOIN_)					(_____	6.3V YELLOW (2)	
)					(_____		
BROWN	250V	_____)					(_____		

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

```

BLUE/BROWN = 240V
BLUE/RED   = 220V
BLUE/WHITE = 200V
    
```

You will note that the Primary is built up in sections and the two wires in the Blue, White and Red sleeves **must always be individually joined** to make the primary circuit complete. Spare connections not required can be cut short, joined and isolated. The solid wire inside the sleeving is coated with polyurethane and needs to be **stripped away and tinned** if the leads are shortened.