

**0545**

BLACK	0V	_____	) :	( _____	0V ORANGE (1)	
			)	( _____		0.45A
			) :	( _____	365V ORANGE (1)	
			)	( _____		
			) :	( _____	0V ORANGE (2)	
			)	( _____		0.45A
			) :	( _____	365V ORANGE (2)	
			)	( _____		
			) :	( _____	0V PINK	
			)	( _____		0.5A
			) :	( _____	40V PINK	
			)	( _____		
			) :	( _____	0V YELLOW	
			)	( _____		6A
			) :	( _____	6.3V YELLOW	
BROWN	230V	_____	) :	( _____		
			)	( _____	0V VIOLET	
			) :	( _____		10A
			)	( _____	5V VIOLET	
			) :	( _____		
YELLOW/GREEN		_____	) :	ELECTROSTATIC SCREEN		

FOR FLEXIBLE LEADS PRIMARY - just cut short and isolate (INDIVIDUALLY) any spare connections

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.