

## **Connection Diagram**



EU Primary	,	WW Prime	ary				
240	Brown	115V	Brown	>	- Orange	190V	0.85A max.
230V	Red		$\longrightarrow$ $\parallel$		-		
210V	White —		3	<u> </u>	- Pink	24V	0.5A max.
	} <b>o</b> /R	0V	Black		-		
		115V	Red———		Yellow 1	6.3V	6A max.
10V	Blue		3	>	Yellow 2	6.3V	3A max.
0V	Black————————————————————————————————————	0v	Blue————————————————————————————————————		-		
	Yel/Grn Electrostatic	Screen	Yel/Grn				

## **Notes**

Visual identification – Worldwide version has two white leads, European version has one.

## Worldwide connection options:

- $\bullet$  110v N: join Blue and Black, L: join White 1 and White 2, isolate Red and Brown
- $^{\bullet}$  120v – N: join Blue and Black, L: join Red and Brown, isolate White 1 and White 2
- $\bullet$  240v N: Blue, L: Brown, join Red and Black, isolate White 1 and White 2 European connection options:

For mains voltages of 210v, 230v or 250v use Black as Neutral. For 200v, 220v or 240v, use Blue.

ALWAYS isolate all unused leads SEPERATELY FROM EACH OTHER