

Connection Diagram Type: 0714

EU Primary		WW Primary			
250V	Brown	120V Brown	Orange	380V	0.25A max.
230V 210V	Red ————————————————————————————————————	110V White 2	Yellow	6.3V	2A max.
		120V Red————————————————————————————————————	Orange	16V	2A max.
10V 0V	Blue ————————————————————————————————————	Ov Blue	Pink	24V	0.5A max.
	Yel/Grn Electrostatic	creen Yel/Grn			

Notes

 $\label{lem:visual} \mbox{ Visual identification} - \mbox{Worldwide version has two white leads, European} \\ \mbox{version has one.}$

Worldwide connection options:

- \bullet 110v N: join Blue and Black, L: join White 1 and White 2, isolate Red and Brown
- \bullet 120v – N: join Blue and Black, L: join Red and Brown, isolate White 1 and White 2
- 240v N: Blue, L: Brown, join Red and Black, isolate White 1 and White 2 European connection options:

For mains voltages of 210v, 230v or 250v use Black as Neutral. For 200v, 220v or 240v, use Blue.

ALWAYS isolate all unused leads SEPERATELY FROM EACH OTHER