

Connection Diagram Type: 0728

EU Primary		WW Primary	
250V	Brown —	120V Brown Orange	360V
230V	Red	110V White 2———— Grey	0V 0.25A max.
210V	White) Orange	360V
	} o R	OV Black————————————————————————————————————	5V 3A max.
	} /	120V Red———	
4014	}	110V White 1————————————————————————————————————	5V 4A max.
10V	Blue	→ —	
0V	Black	Ov Blue Orange	10V 2A max.

Notes

 $\label{thm:continuous} \mbox{ Visual identification} - \mbox{Worldwide version has two white leads, European version has one. }$

Worldwide connection options:

- \bullet 110v N: join Blue and Black, L: join White 1 and White 2, isolate Red and Brown
- $^{\bullet}$ 120v N: join Blue and Black, L: join Red and Brown, isolate White 1 and White 2
- 240v N: Blue, L: Brown, join Red and Black, isolate White 1 and White 2 European connection options:

For mains voltages of 210v, 230v or 250v use Black as Neutral. For 200v, 220v or 240v, use Blue.

ALWAYS isolate all unused leads SEPERATELY FROM EACH OTHER