

Connection Diagram 1

Type: 0743

U Primary			WW Primary		
				Brown —	
245 V	Red		110V	White 2—	\longrightarrow
		} OR	0V	Black—	
		} /	120V	Red—	
		} /	110V	White 1—	$\longrightarrow $
		3/			3 Ⅲ
0V	Black-)	0v	Blue —	
	Yel/Grn	Electrostation	Screen	Yel/Grn	

N	ot	es

 $\label{thm:problem} \mbox{Visual identification} - \mbox{Worldwide version has two white leads, European} \\ \mbox{version has one.}$

Worldwide connection options:

- \bullet 110v N: join Blue and Black, L: join White 1 and White 2, isolate Red and Brown
- $^{\bullet}$ 120v – N: join Blue and Black, L: join Red and Brown, isolate White 1 and White 2
- \bullet 240v N: Blue, L: Brown, join Red and Black, isolate White 1 and White 2 European connection options:

For mains voltages of 210v, 230v or 250v use Black as Neutral. For 200v, 220v or 240v, use Blue.

ALWAYS isolate all unused leads SEPERATELY FROM EACH OTHER

	– Orange	260V	
<u></u>	– Grey	0V	0.06A max.
	– Orange	260V	
	– Pink	250V	
<u></u>	– Grey	0V	0.04A max.
	– Pink	250V	
	Or/Wht	235V	
	– Grey	0V	0.03A max.
	Or/Wht	235V	
\	– Yellow	6.3V	3.5A max.