

## Connection Diagram

**Type:** 0745

EU Primary		WW Primary				
				120V	Brown——	
245 V	Red	$\overline{}$		110V	White —	
		}			3	
		}	<b>O</b> R	0V	Black———	
		)		120V	Red——	
		} /		110V	White 1——	
		3/			}	
0V	Black			0v	Blue——	
	Yel/Grn	Electrost	tatic Scree	en	Yel/Grn	-:

## **Notes**

Visual identification – Worldwide version has two white leads, European version has one.

## **Worldwide connection options:**

- $\bullet$  110v N: join Blue and Black, L: join White 1 and White 2, isolate Red and Brown
- $^{\bullet}$  120v – N: join Blue and Black, L: join Red and Brown, isolate White 1 and White 2
- 240v N: Blue, L: Brown, join Red and Black, isolate White 1 and White 2 European connection options:

For mains voltages of 210v, 230v or 250v use Black as Neutral. For 200v, 220v or 240v, use Blue.

ALWAYS isolate all unused leads SEPERATELY FROM EACH OTHER

>	– Orange	250V		
	– – Grey	0V	0.23A max.	
	– Pink	50V		
	– Orange	250V		
	– Purple	2.5V		
	- Green	0V	3A max.	
	– Purple	2.5V		
	- Yellow	3.15V		
	– Green	0V	6A max.	
	– Yellow	3.15V		