

0928

BLACK	0V	_____)	(_____	360V RED/BLACK	720V ct @ 0.3A
)	(_____	0V GREEN	
BROWN	230V	_____)	(_____		
)	(_____	360V RED/BLACK	
BLACK	0V	_____)	(_____	0V YELLOW (1)	6.3V ct @ 3.5A
RED	10V	_____)	(_____ct	GREEN (1)	
)	(_____	6.3V YELLOW (1)	
)	(_____	0V YELLOW (2)	6.3V ct @ 3.5A
)	(_____ct	GREEN (2)	
)	(_____	6.3V YELLOW (2)	
)	(_____	0V YELLOW (3)	6.3V ct @ 3.5A
)	(_____ct	GREEN (3)	
)	(_____	6.3V YELLOW (3)	
)	(_____	0V YELLOW (4)	6.3V ct @ 3.5A
)	(_____ct	GREEN (4)	
)	(_____	6.3V YELLOW (4)	
)	(_____	0V GREY	10V @ 0.3A
)	(_____	10V GREY	

NOTE: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.