

7918

BLACK	0V)	(0V	YELLOW	0.25A
)	(
BLUE	10V)	(260V	YELLOW	
)	(
)	(0V	GREY	0.25A
)	(ct	VIOLET	
)	(
)	(260V	GREY	
WHITE	210V)	(0V	ORANGE (1)	6A
)	(
)	(11V	ORANGE (1)	
RED	230V)	(0V	ORANGE (2)	6A
)	(
)	(11V	ORANGE (2)	
BROWN	250V)	(0V	GREEN	3A
)	(
)	(10V	GREEN	

To obtain other inputs use as follows:

10V tap in place of 0V terminal thus:

BLUE/BROWN = 240V BLUE/RED = 220V BLUE/WHITE = 200V